



Low Loss N Male to RP SMA Male Cable LMR-240 Coax

The type N male to RP SMA male cable using LMR-240 coax, part number FMC00441, from Fairview Microwave is in-stock and ships same day. This Fairview type N to reverse polarity SMA cable assembly has a male to male gender configuration with 50 ohm flexible LMR-240 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00441 type N male to reverse polarity SMA male cable assembly operates to 6 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description		Min	Т	ур	Max	ι	Jnits	
Frequency Range		DC			6		GHz	
VSWR					1.35:1			
Velocity of Propagation			8	34			%	
RF Shielding		90					dB	
Group Delay			1.21	[3.97]		ns/f	t [ns/m	<u>1]</u>
Capacitance			24.2	[79.4]		pF/f	t [pF/m	<u>1]</u>
Inductance			0.06 [0.2]		uH/ft [uH/m]			
DC Resistance Inner Conductor			3.2	[10.5]		Ω/100	Oft [Ω/k	(m]
DC Resistance Outer Cor	nductor		3.89	[12.76]		Ω/100	Oft [Ω/k	(m]
Jacket Spark					5,000	\	/rms	

Mechanical Specifications

Cable Assembly

Diameter 0.312 in [7.92 mm]

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1
Shield Layer 2
Jacket Material
Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius Bending Moment Flat Plate Crush

Tensile Strength

0.75 in [19.05 mm] 2.5 in [63.5 mm] 0.25 lbs-ft [0.34 N-m] 20 lbs/in [0.36 Kg/mm] 80 lbs [36.29 Kg]

LMR-240

50 Ohms

Solid

Copper

PE (F)

PE, Black

Aluminum Tape

Tinned Copper Braid

0.24 in [6.1 mm]



Configuration:

- N Male
- SMA Male Reverse Polarity
- LMR-240

Features:

- Max Frequency 6 GHz
- Shielding Effectivity > 90 dB
- 84% Phase Velocity
- · Double Shielded
- PE Jacket
- N Male to N Male
- Times© LMR-240 Flexible Low Loss Coax
- Heat Shrink Booting
- VoP of 84%
- · Custom lengths available

Applications:

- General Purpose
- Laboratory Use
- General Purpose
- Wireless Communications
- Lab Use
- Equipment Interconnect

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

Description	Connector 1	Connector 2			
Туре	N Male	SMA Male			
Polarity		Reverse Polarity			
Impedance	50 Ohms	50 Ohms			
Contact Material & Plating	Gold	Gold			
Dielectric Type	PTFE	PTFE			
Body Material & Plating	Brass, Gold	Brass, Gold			
Coupling Nut Material & Plating	Brass, Gold	Brass, Gold			
Hex Size	5/16 in.	5/16 in.			
Torque	5 in-lbs 0.57 Nm	5 in-lbs 0.57 Nm			


Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:



Example: FMC00441-12 = 12 inches long cable

FMC00441-100cm = 100 cm long cable

Low Loss N Male to RP SMA Male Cable LMR-240 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss N Male to RP SMA Male Cable LMR-240 Coax FMC00441

URL: https://www.fairviewmicrowave.com/low-loss-n-male-sma-male-cable-Imr240-coax-fmc00441-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





