

FMC00442-48 DATA SHEET

N Male to RP SMA Female Cable LMR-240 Coax in 48 Inch

The type N male to RP SMA female 48 inch cable using LMR-240 coax, part number FMC00442-48, from Fairview Microwave is in-stock and ships same day. This Fairview type N to reverse polarity SMA cable assembly has a male to female gender configuration with 50 ohm flexible LMR-240 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00442-48 type N male to reverse polarity SMA female cable assembly operates to 6 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	ι	Jnits	
Frequency Range	DC			6		GHz	
VSWR				1.35:1			
Velocity of Propagation		8	34			%	
RF Shielding	90					dB	
Group Delay		1.21	[3.97]		ns/f	t [ns/n	<u>1]</u>
Capacitance		24.2	[79.4]		pF/f	t [pF/n	n]
Inductance		0.06	[0.2]		uH/f	t [uH/r	n]
DC Resistance Inner Cor	nductor	3.2	[10.5]		Ω/100	Oft [Ω/ŀ	(m)
DC Resistance Outer Cor	nductor	3.89	[12.76]		Ω/100	Oft [Ω/ŀ	(m)
Jacket Spark				5,000	١	/rms	

Mechanical Specifications

Cable Assembly

Length* 48 in [121.92 cm]
Diameter 0.312 in [7.92 mm]

Cable

Cable Type LMR-240 **Impedance** 50 Ohms Inner Conductor Type Solid Inner Conductor Material and Plating Copper Dielectric Type PE (F) Number of Shields 2 Shield Layer 1 Aluminum Tape Shield Layer 2 Tinned Copper Braid

Jacket Material PE, Black
Jacket Diameter 0.24 in [6.1 mm]

One Time Minimum Bend Radius
Repeated Minimum Bend Radius
Bending Moment

0.75 in [19.05 mm]
2.5 in [63.5 mm]
0.25 lbs-ft [0.34 N-m]



Configuration:

- N Male
- SMA Female Reverse Polarity
- LMR-240

Features:

- Max Frequency 6 GHz
- Shielding Effectivity > 90 dB
- 84% Phase Velocity
- · Double Shielded
- PE Jacket
- N Male to N Male
- Times© LMR-240 Flexible Low Loss Coax
- · Heat Shrink Booting
- VoP of 84%
- · Custom lengths available

Applications:

- General Purpose
- Laboratory Use
- General Purpose
- Wireless Communications
- Lab Use
- Equipment Interconnect

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Flat Plate Crush Tensile Strength 20 lbs/in [0.36 Kg/mm] 80 lbs [36.29 Kg]

Connectors

Description	Connector 1	Connector 2			
Туре	N Male	SMA Female			
Polarity		Reverse Polarity			
Impedance	50 Ohms	50 Ohms			
Contact Material & Plating	Gold	Gold			
Dielectric Type	PTFE	PTFE			
Body Material & Plating	Brass, Tri-Metal	Brass, Gold			

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:



Example: FMC00442-12 = 12 inches long cable

FMC00442-100cm = 100 cm long cable

N Male to RP SMA Female Cable LMR-240 Coax in 48 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: N Male to RP SMA Female Cable LMR-240 Coax in 48 Inch

URL: https://www.fairviewmicrowave.com/n-male-sma-female-cable-lmr240-coax-fmc00442-48-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





