



SMPS Female to 2.92mm Male Cable FM-P047HF Coax

The SMPS female to 2.92mm male cable using FM-P047HF coax, part number FMCA9954, from Fairview Microwave is in-stock and ships same day. This Fairview SMPS to 2.92mm cable assembly has a female to male gender configuration with 50 ohm flexible FM-P047HF coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA9954 SMPS female to 2.92mm male cable assembly operates to 40 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	ι	Inits
Frequency Range	DC			40		GHz
VSWR				1.4:1		
Velocity of Propagation			70			%
RF Shielding	90					dB
Capacitance		29 [95.14]		pF/fl	t [pF/m]

Specifications by Frequency

Part Number	Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
Fait Nullibel	Length	Frequency	2500	5000	10000	20000	40000	MHz	weight (ibs)
FMCA9954	Custom Lengths	Insertion Loss (Typ.)	0.55	0.8	1.17	1.78	2.77	dB/ft	
FIVICA9954	Available	ilisertion Loss (Typ.)	1.81	2.63	3.84	5.84	9.09	dB/m	
FMCA9954-6	6 inch	Insertion Loss (Typ.)	0.5	0.72	1.03	1.52	2.28	dB	0.009
FMCA9954-12	12 inch	Insertion Loss (Typ.)	0.78	1.12	1.62	2.41	3.66	dB	0.011
FMCA9954-18	18 inch	Insertion Loss (Typ.)	1.05	1.52	2.2	3.3	5.05	dB	0.013

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

0.1xSORT(fGHz) dB Loss due to Connector 1: 0.04xSQRT(fGHz) dB Loss due to Connector 2: Base Weight: 0.011 pounds Additional Weight per Inch: 0.00033 pounds

Mechanical Specifications

Cable Assembly

Weight 0.01411 lbs [6.4 g]

Cable

Cable Type **Impedance** Inner Conductor Type Inner Conductor Material and Plating Dielectric Type Number of Shields Shield Layer 1 Shield Layer 2 Jacket Material

FM-P047HF 50 Ohms Solid Copper, Silver

PTFE

Silver Plated Copper Tape Silver Plated Copper Braid

FEP, Blue



Configuration:

- SMPS Female
- 2.92mm Male
- FM-P047HF


Features:

- Max Frequency 40 GHz
- Shielding Effectivity > 90 dB
- 70% Phase Velocity
- Double Shielded
- FEP Jacket

Applications:

- General Purpose
- Laboratory Use
- Scientific research
- High-reliability, high-density for aerospace & defense application
- Ground base station & communication systems, avionics, radar systems

Cable Diagram:



Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Jacket Diameter 0.06 in [1.52 mm]

Repeated Minimum Bend Radius 0.1 in [2.54 mm]

Connectors

Description	Connector 1	. Connect	Connector 2				
Туре	SMPS Female Pus	h-on 2.92mm Male	Threaded				
Impedance	50 Ohms	50 Ohr	ns				
Contact Material & Plating	Beryllium Copper, (GoldBeryllium Copper, (Gold over N				
Contact Plating Spec.	50 μin minimun	n 50 µin min	imum				
Dielectric Type	PTFE	PEI					
Outer Cond Material & Plati	ng Beryllium Copper, (Gold					
Outer Cond Plating Spec.	50 μin minimun	n					
Body Material & Plating	Beryllium Copper, (GoldBeryllium Copper, (Gold over N				
Body Plating Spec.	30 μin minimun	n 50 µin min	imum				
Coupling Nut Material & Pla	ting	Passivated Stair	nless Steel				
Coupling Nut Plating Spec.		ASTM-AS	582				

Environmental Specifications

Temperature

Operating Range

-55 to +165 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:

FMCA9954 - xx uu | cm = Centimeters | chlank> = Inches | Length

Example: FMCA9954-12 = 12 inches long cable

FMCA9954-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020 REV 1.0 Page 2 of 4





SMPS Female to 2.92mm Male Cable FM-P047HF Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: SMPS Female to 2.92mm Male Cable FM-P047HF Coax FMCA9954

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

URL: https://www.fairviewmicrowave.com/smps-female-to-2.92mm-male-cable-fm-p047hf-coax-fmca9954-p.aspx

to implem	ent improv	ements.	Fairview	Microw	ave reserv	es the rigl	nt to mak	ke such	changes	as req	quired	d. Unles	s ot	herwise
stated, all	specification	ons are	nominal.	Fairvie	w Microwa	ve does n	ot make	any re	presentat	ion or	war	ranty re	gard	ling the
suitability	of the part	describ	ed hereir	n for any	/ particulai	r purpose,	and Fair	view M	1icrowave	does	not a	assume	any	liability
arising ou	t of the use	of any	part or do	ocument	ation.									

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





