

BMMA Female (Jack) PCB Connector 0.072 inch Edge Launch Solder Attachment



FMCN5135

Configuration

- BMMA Female Connector
- 50 Ohms
- Straight Body Geometry
- Connector Interface Types: 0.072 inch Edge Launch

Features

- Operating Frequency of 18 GHz Max.
- Good VSWR of 1.35:1
- Gold Plated Beryllium Copper Contact

Applications

- General Purpose Test
- PCB Applications

Description

BMMA Female Standard Connector Solder Attachment for 0.072 inch Edge Launch Cable, part number FMCN5135, from Fairview Microwave is in-stock and ships same day. This BMMA female connector operates up to a maximum frequency of 18 GHz and offers good VSWR of 1.35:1.

Fairview's BMMA female connector FMCN5135 datasheet specifications and outline drawing are shown in this PDF below. Our extensive offering of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. From providing an I/O for a board design to creating a custom cable assembly configuration, Fairview Microwave has a connector solution to meet your needs. Fairview Microwave also has the expertise to build your custom cable assemblies for you and ship them same-day.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		18	GHz
VSWR			1.35:1	
Insertion Loss			0.509	dB
Impedance		50		Ohms

Mechanical Specifications

Size

Length	0.5 in [12.7 mm]
Width	0.24 in [6.1 mm]
Height	0.24 in [6.1 mm]
Weight	0.005 lbs [2.27 g]
Mating Cycles	500 Cycles

Material Specifications

Description	Material	Plating
Contact	Beryllium Copper	Gold
Insulation	PTFE	
Outer Conductor	Stainless Steel	
Body	Stainless Steel	Gold

BMMA Female (Jack) PCB Connector 0.072 inch Edge Launch Solder Attachment



FMCN5135

Environmental Specifications

Temperature

Operating Range

-65 to +165 deg C

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

BMMA Female (Jack) PCB Connector 0.072 inch Edge Launch Solder Attachment from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [BMMA Female \(Jack\) PCB Connector 0.072 inch Edge Launch Solder Attachment FMCN5135](#)

URL: <https://www.fairviewmicrowave.com/bmma-female-pcb-connector-fmcn5135-p.aspx>

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

FMCN5135 CAD Drawing

BMMA Female (Jack) PCB Connector 0.072 inch Edge Launch Solder Attachment

