

## Matching Pad 50 Ohm BNC Male to 75 Ohm BNC Female Operating from DC to 3 GHz

Fairview Microwave's FMMP1100 is a 50 ohm BNC male to 75 ohm BNC female matching pad that operates from DC to 3 GHz. This BNC to BNC impedance matching pad offers a low VSWR of 1.25:1 max and attenuation of 7.5 dB max. FMMP1100 50 ohm to 75 ohm minimum loss pad has a maximum CW power rating of 0.5 Watt. Matching pads are used to match the different impedance between two devices, maximizing power transfer between the two impedances. Fairview Microwave's minimum loss impedance matching pads are available in various connector combinations to fit your needs, all of which ship the same day.



### Electrical Specifications

Description	Min	Typ	Max	Units
Frequency Range	DC		3	GHz
VSWR		1.15:1	1.25:1	
Attenuation		4	7.5	dB
Input Power, CW			0.5	Watts

### Mechanical Specifications

#### Size

Length	2.09 in [53.09 mm]
Width	0.57 in [14.48 mm]
Height	0.57 in [14.48 mm]
Weight	0.04 lbs [18.14 g]
Housing Material and Plating	Brass, Tri-Metal

#### Connector 1

Description	Connector
Type	BNC Male
Impedance	50 Ohms
Inner Conductor Material and Plating	Brass, Gold
Body Material and Plating	Brass, Tri-Metal

#### Connector 2

Description	Connector
Type	BNC Female
Impedance	75 Ohms
Inner Conductor Material and Plating	phosphor bronze, Gold
Body Material and Plating	Brass, Tri-Metal

### Configuration:

- Connector 1: 50 Ohms BNC Male
- Connector 2: 75 Ohms BNC Female

### Features:

- DC to 3 GHz Frequency Range
- Low VSWR < 1.25:1
- 0.5 W Max Power (CW)

### Applications:

- CATV / Cable Networks
- Test and Measurement
- Communication Systems
- Wireless Systems

Fairview Microwave  
 301 Leora Ln., Suite 100  
 Lewisville, TX 75056  
 Tel: 1-800-715-4396 / (972) 649-6678  
 Fax: (972) 649-6689  
[www.fairviewmicrowave.com](http://www.fairviewmicrowave.com)  
[sales@fairviewmicrowave.com](mailto:sales@fairviewmicrowave.com)

**Compliance Certifications** (see [product page](#) for current document)

**Plotted and Other Data**

Notes:

Matching Pad 50 Ohm BNC Male to 75 Ohm BNC Female Operating from DC to 3 GHz from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [Matching Pad 50 Ohm BNC Male to 75 Ohm BNC Female Operating from DC to 3 GHz FMMP1100](#)

URL: <https://www.fairviewmicrowave.com/matching-pad-bnc-bnc-3-mhz-fmmp1100-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

