

WR-75 Bandpass Waveguide Filter With a 13.75 GHz to 14.5 GHz Pass Band

The FMW75F001 is a WR-75 bandpass filter with UG Cover and UG Grooved Flanges. The pass band is 750 MHz, or 13.75 to 14.5 GHz. Implementing a waveguide design, the filter has excellent rejection of 60 dB minimum at 10.75 GHz to 12.75 GHz and 45 dB minimum at 16 GHz to 18 GHz, or about 1000 MHz and 1500 MHz from the band edge. It has a maximum insertion loss of 0.5 dB.

Electrical Specifications (Values at 25°C, sea level)

Description	Min	Typ	Max	Units
Passband Frequency Range	13.75	-	14.5	GHz
Insertion Loss			0.5	dB
Passband VSWR			1.25:1	
Input Power			200	Watts
Peak Power			20	kWatts
L-Band Rejection 12.75 GHz	60			dB
H-Band Rejection 16 GHz	45			dB

Mechanical Specifications

Size

Length	7.87 in [199.9 mm]
Width	1.5 in [38.1 mm]
Height	1.5 in [38.1 mm]
Weight	0.65 lbs [294.84 g]

Flange 1

Waveguide Size	WR-75
Flange Material and Plating	Aluminum, Silver
Flange 1 Type	UG Cover

Flange 2


Waveguide Size	WR-75
Flange Material and Plating	Aluminum, Silver
Flange 2 Type	UG Grooved

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at 25 °C, sea level



Configuration:

- Passband: Band Pass
- Flange 1: WR-75
- Flange 2: WR-75

Features:

- Passband of 750 MHz
- 13.75 GHz to 14.5 GHz Passband
- WR-75 UG Cover and Grooved Flanges
- Min rejection 60 dB at 10.75 to 12.75 GHz
- Min rejection 45 dB at 16 to 18 GHz
- Maximum Insertion Loss of 0.5 dB
- Max Power (CW) 200 Watts

Applications:

- Radar Systems
- Test and Measurement
- Satellite Communications
- Instrumentation
- Automotive Radar Systems

Fairview Microwave
 301 Leora Ln., Suite 100
 Lewisville, TX 75056
 Tel: 1-800-715-4396 / (972) 649-6678
 Fax: (972) 649-6689
www.fairviewmicrowave.com
sales@fairviewmicrowave.com

WR-75 Bandpass Waveguide Filter With a 13.75 GHz to 14.5 GHz Pass Band from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [WR-75 Bandpass Waveguide Filter With a 13.75 GHz to 14.5 GHz Pass Band FMW75F001](#)

URL: <https://www.fairviewmicrowave.com/wr-75-waveguide-bandpass-filter-ug-pass-band-fmw75f001-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.



