

WR-51 Seamless Flexible Waveguide Using Square Cover Flange With a 15 GHz to 22 GHz Frequency Range

The SMW51SF005-36 is part of Fairview Microwave's family of flexible, seamless waveguides which operates in the 15 to 22 GHz range. The waveguide body is made of silver plated brass. It can be bent in both the E and H planes without impairing VSWR or attenuation. The waveguide is covered by a neoprene jacket which protects the waveguide and provides mechanical support.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	15		22	GHz
VSWR		1.1:1		
Insertion Loss		0.54		dB

Mechanical Specifications

Waveguide Size	
Waveguide Design	
Section Length	
E-Plane Minimum Bend	Radius, One Time
H-Plane Minimum Bend	Radius, One Time
Maximum Offset Rotation	on, One Time

WR-51 Seamless
36 in [914.4 mm]
0.59 in [14.99 mm]
0.98 in [24.89 mm]
45 degrees/ft
15 degrees/re

Description	Flange 1	Waveguide	Flange 2	
Туре	Square Cover	WR-51	Square Cover	
Designation	None	None		
Material	Brass	Copper	Brass	
Plating		Silver		
Color	Gold	Black	Gold	

Compliance Certifications (visit www.FairviewMicrowave.com for current

document)	
RoHS Compliant	Yes
REACH Compliant	12/17/2015

Plotted and Other Data

- Notes:
- Notes, Plotted Data

SMW51SF005-36 DATA SHEET



Features:

- WR-51 waveguide
- Flexes in both the E and H plane
- 15 GHz to 22 GHz
 Frequency Range
- Brass flanges with a silver plated brass body
- Neoprene sleeve provides added protection and mechanical support

Applications:


- Allows expansion/contraction due to thermal issues.
- Test Benches
- Microwave Radio
- Eliminates installation problems caused by misalignment.
- Pressurized waveguide systems
- Provides vibration isolation

Fairview Microwave 1130 Junction Dr. #100 Allen, TX 75013 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Typical Performance Data



WR-51 Seamless Flexible Waveguide Using Square Cover Flange With a 15 GHz to 22 GHz Frequency Range from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: WR-51 Seamless Flexible Waveguide Using Square Cover Flange With a 15 GHz to 22 GHz Frequency Range SMW51SF005-36


URL: https://www.fairviewmicrowave.com/wr-51-seamless-flexible-waveguide-square-15-22-ghz-smw51sf005-36-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689







FAIRVIEW MICROWAVE INC.	NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].					
WR-51 Seamless Flexible Waveguide Using Square Cover Flange With a 15 GHz to 22 GHz Frequency Range	DWG NO SMW51SF005-36			CAGE CODE 3FKR5		
	CAD FILE 101315	SHEET	SCALE	N/A	SIZE A	2233

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689