

Tool Kit, Install Tool Kit for LMR-400/600 Connectors (CST-400,CST-600, CT-U, Y1719, Y1720, CCT-02, FKP-01)



Configuration

Tool Type	LMR Cable Tool Kit
Hex Size, in	0.429, 0.610
Kit Contents	CST-400,CST-600, CT-U, Y1719, Y1720, CCT-02, FKP-01

Mechanical Specifications

Size	
Length	12 in [304.8 mm]
Width	7.5 in [191 mm]
Height	2 in [50.8 mm]
Weight	3.15 lbs [1.43 kg]

Compliance Certifications (see [product page](#) for current document)

Notes:

- Values at 25 °C, sea level

Tool Kit, Install Tool Kit for LMR-400/600 Connectors (CST-400,CST-600, CT-U, Y1719, Y1720, CCT-02, FKP-01) from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [Tool Kit, Install Tool Kit for LMR-400/600 Connectors \(CST-400,CST-600, CT-U, Y1719, Y1720, CCT-02, FKP-01\) TK-01](#)

URL: <https://www.fairviewmicrowave.com/tool-kit-install-tool-kit-for-lmr-400-600-conn-cst-400-cst-600-ct-u-y1719-y1720-cct-02-fkp-01-tk-01-p.aspx>


The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

Fairview Microwave
 301 Leora Ln., Suite 100
 Lewisville, TX 75056
 Tel: 1-800-715-4396 / (972) 649-6678
 Fax: (972) 649-6689
www.fairviewmicrowave.com
sales@fairviewmicrowave.com

ZONE	REV	DESCRIPTION	DATE	CHANGED BY	APPROVED
A		INITIAL RELEASE	03/21/2023	HBAKKE	AGANWANI

PART NUMBER	QUANTITY	DESCRIPTION
CST-400	1	PREP TOOL FOR LMR-400
CST-600	1	PREP TOOL FOR LMR-600
CT-U	1	CRIMP TOOL FOR Y SERIES DIES
Y1719	1	.429" HEX DIES FOR TC/EZ400 CRIMP CONNECTORS
Y1720	1	.610" HEX DIES FOR TC/EZ600 CRIMP CONNECTORS
CCT-02	1	CABLE CUTTING TOOL
FKP-01	1	FIELD KIT TOOL POUCH

UNLESS OTHERWISE SPECIFIED, LEADING DIMENSIONS ARE INCHES AND DIMENSIONS IN [] ARE MILLIMETERS
<p>TOLERANCES:</p> <p>.X = ±.2 [.5] FRACTIONS ± 1/32</p> <p>.XX = ±.02 [.5] ANGLES ± 1°</p> <p>.XXX = ±.005 [.13]</p> <p>CABLE LENGTH TOLERANCES:</p> <p>512 (305) = +1 (25) / -0</p> <p>>12 (305) ≤ 60 (1524) = +2 (51) / -0</p> <p>>60 (1524) ≤ 120 (3048) = +4 (102) / -0</p> <p>>120 (3048) ≤ 300 (7620) = +6 (152) / -0</p> <p>>300 (7620) = +5% / -0</p>
<p>ALL DIMENSIONS ARE FOR REFERENCE ONLY AND SUBJECT TO CHANGE WITHOUT NOTICE</p>

FAIRVIEW MICROWAVE [®]	an INFINIT [®] brand
<p>Website: www.FairviewMicrowave.com</p> <p>Phone: 1.800.715.4396 1.972.649.6678</p>	
 <p>INTERPRET ALL DIMENSIONS AND TOLERANCES PER ASME Y14.5</p>	<p>SCALE: NONE</p> <p>SHEET: 1 OF 1</p>

DESCRIPTION	SIZE	CAGE CODE	DRAWN BY	ITEM NO.	REV
Tool, install tool kit for LMR-400/600 Conn (CST-400,CST-600, CT-U, Y1719, Y1720, CCT-02, FKP-01)	A	3FKR5	HBAKKE	TK-01	A