

FMAD1276 DATA SHEET

RA 1.85mm Male to 1.85mm Female Adapter with Passivated Stainless Steel Body

RA 1.85mm male to 1.85mm female adapter part number FMAD1276 from Fairview Microwave is in-stock and ships same day. This Fairview 1.85mm to 1.85mm adapter has a male to female gender configuration and is built of durable stainless steel. FMAD1276 1.85mm male to 1.85mm female adapter operates to 67 GHz. The Fairview Microwave RF adapter provides good VSWR of 1.35:1 maximum. The 1.85mm connector mates mechanically with commercially available 2.4mm connectors. This right angle 1.85mm adapter allows for easier connections in tight spaces.

RF adapters can be used to enable connections between two connector types that would otherwise not mate. Certain RF adapter configurations can also be used to protect connectors on expensive equipment where the number of connect and disconnect cycles is high. An RF, microwave, or millimeter wave adapter is connected to the equipment and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Fairview Microwave also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	DC		67	GHz
VSWR			1.35:1	

Mechanical Specifications

December 1	C	6
Weight		0.216 lbs [97.98 g]
Width Height		0.313 in [7.95 mm] 0.597 in [15.16 mm]
Length		0.687 in [17.5 mm]
3120		

Description	Connector	Connector 2	
Туре	1.85mm Ma	ale 1.85mm Female	
Polarity	Standard	l Standard	

Material Specifications

Description	Connector 1	Connector 2	
Туре	1.85mm Male	1.85mm Female	
Contact Material	Beryllium Copper	Beryllium Copper	
Contact Plating	Gold	Gold	
Contact Plating Spec.	50 μin	50 μin	
Insulation Material	PEI	PEI	
Outer Contact Material		Passivated Stainless Steel	
Body Material	Passivated Stainless Steel	Passivated Stainless Steel	
Coupling Nut Material	Passivated Stainless Steel		

\$ 9121 2 9121

Configuration:

- 1.85mm Male Connector 1
- 1.85mm Female Connector 2
- 50 Ohm
- Right Angle Body Geometry

Features:

- VSWR of 1.35:1 max up to 67 GHz
- 50 µin contact plating
- Gold Plated Beryllium Copper Contact

Applications:

General Purpose Test

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

RA 1.85mm Male to 1.85mm Female Adapter with Passivated Stainless Steel Body from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: RA 1.85mm Male to 1.85mm Female Adapter with Passivated Stainless Steel Body FMAD1276

URL: https://www.fairviewmicrowave.com/ra-1.85mm-male-to-1.85mm-female-adapter-with-passivated-stainless-steel-body-fmad1276-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.





