



## N Male to RA N Male Cable LMR-400 Coax

The type N male to RA type N male cable using LMR-400 coax, part number FMC00160, from Fairview Microwave is in-stock and ships same day. This Fairview type N to type N cable assembly has a male to male gender configuration with 50 ohm flexible LMR-400 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00160 type N male to type N male cable assembly operates to 6 GHz. The right angle type N interface on the LMR-400 cable allows for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

# **Electrical Specifications**

Description	Min	Т	Typ Max		Units		
Frequency Range	DC			6		GHz	
VSWR				1.4:1			
Velocity of Propagation		3	35			%	
RF Shielding	90					dB	
Group Delay	1.2 [3.94]			ns/ft [ns/m]			
Capacitance		23.9 [78.41]			pF/ft [pF/m]		
Inductance		0.06 [0.2]			uH/ft [uH/m]		
DC Resistance Inner Cor	1.39 [4.56]		Ω/1000ft [Ω/Km]				
DC Resistance Outer Cor	1.65	[5.41]		Ω/1000ft [Ω/Km]			
Jacket Spark				8,000	\	/rms	

## **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	6	GHz
Insertion Loss (Typ.)	0.02	0.03	0.04	0.06	0.11	dB/ft
	0.07	0.1	0.13	0.2	0.36	dB/m

## **Electrical Specification Notes:**

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

# **Mechanical Specifications**

### **Cable Assembly**

Diameter 0.827 in [21.01 mm]

#### Cable

Cable Type LMR-400



# **Configuration:**

- N Male
- N Male Right Angle
- LMR-400

## **Features:**

- Max Frequency 6 GHz
- Shielding Effectivity > 90 dB
- 85% Phase Velocity
- · Double Shielded
- PE Jacket

# **Applications:**

- General Purpose
- · Laboratory Use
- Antenna Installations
- Land Mobile Radio & Other Communication Systems
- Cellular & Wi-Fi Systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





50 Ohms Impedance Inner Conductor Type Solid

Inner Conductor Material and Plating Copper Clad Aluminum

PE (F) 2

Number of Shields

Shield Layer 1 Shield Layer 2 Jacket Material

Jacket Diameter

Dielectric Type

PE, Black 0.405 in [10.29 mm]

Tinned Copper Braid

Aluminum Tape

One Time Minimum Bend Radius Repeated Minimum Bend Radius

Bending Moment Flat Plate Crush Tensile Strength

1 in [25.4 mm] 4 in [101.6 mm] 0.5 lbs-ft [0.68 N-m] 40 lbs/in [0.71 Kg/mm]

160 lbs [72.57 Kg]

### **Connectors**

Description	Connector 1	Connector 2				
Туре	N Male	N Male				
Impedance	50 Ohms	50 Ohms				
Contact Material & Plating	Brass, Gold	Beryllium Copper, Gold				
Contact Plating Spec.	3 µin minimum	1.27 µm minimum				
Dielectric Type	PTFE	PTFE				
Body Material & Plating	Brass, Nickel	Brass, Tri-Metal				
Body Plating Spec.	100 μin minimum	n 2 μm minimum				
Coupling Nut Material & Pla	ting Brass, Nickel	Brass, Tri-Metal				
Coupling Nut Plating Spec.	100 μin minimum	n 2 μm minimum				
Torque		44 in-lbs 4.97 Nm				

Mechanical Specification Notes:

## **Environmental Specifications**

**Temperature** 

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

**Compliance Certifications** (see product page for current document)

### **Plotted and Other Data**

Notes:

### **How to Order**

Part Number Configuration: FMC00160 - xx cm = Centimeters <br/>
<br/>
dlank> = Inches - Length

Example: FMC00160-12 = 12 inches long cable

FMC00160-100cm = 100 cm long cable

<sup>\*</sup>All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.





N Male to RA N Male Cable LMR-400 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

Click the following link to obtain additional part information: N Male to RA N Male Cable LMR-400 Coax FMC00160

URL: https://www.fairviewmicrowave.com/n-male-ra-n-male-cable-lmr400-coax-fmc00160-p.aspx

to implem	ent improv	ements.	Fairview	Microw	ave reserv	es the righ	nt to mak	ke such	changes	as req	juired. Unle	ess ot	herwise
stated, all	l specificati	ons are	nominal.	Fairvie	w Microwa	ve does n	ot make	any re	presentat	ion or	warranty r	egard	ling the
suitability	of the par	t describ	ed hereir	n for any	/ particular	purpose,	and Fair	view M	licrowave	does	not assume	any	liability
arising ou	t of the use	e of any	part or do	ocument	ation.								





