

# FMCP1162 DATA SHEET

# 1.0 mm Directional Coupler, 20 GHz to 110 GHz Rated to 1 Watt

Directional couplers are indispensable components for isolating, separating and combining signals. For example, they provide a simple way of sampling microwave signals. They also can make accurate attenuator measurements since reflections are eliminated. The FM2CP1162 is a directional coupler that operates from 20 to 110 GHz and can handle up to 1 Watt (CW) with 7 dB directivity minimum and 1.4:1 VSWR typical. The package interface uses 1.0 mm (W1) female connectors.

The FMCP1162 is part of Fairview Microwave's family of directional/dual-directional couplers that offer coupling ratios up to 50 dB with excellent performance featuring high directivity, low insertion loss and VSWR. They are available in both narrow and broad bandwidths and can be used in a wide variety of applications including signal sampling, VSWR measurements, power combining and distribution.

## **Electrical Specifications**

Description	Min	Тур	Max	Units
Frequency Range	20		110	GHz
Impedance		50		Ohms
Coupling		17 ±8		dB
Insertion Loss			5.5	dB
Directivity	7			dB
Isolation	23			dB
Input Power (CW)			1	Watt

### **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency Range	20-25	25-50	50-65	65-80	80-110	GHz
Insertion Loss, Max	2.3	2.3	3.7	3.7	5.5	dB
Main Line VSWR, Max	1.4:1	1.9:1	1.9:1	1.9:1	1.9:1	
Directivity, Min	7	7	10	10	7	dB
Coupling, Typ	20	15	12.5	11	11	dB
Frequency Sensitivity, Ty	/p ±5	±5	±3.5	±2	±2	dB
Isolation, Min	24	24	23	23	23	dB

# **Mechanical Specifications**

Size

Length 1.23 in [31.24 mm]
Width/Dia. 0.354 in [8.99 mm]
Height 0.886 in [22.5 mm]
Weight 0.035 lbs [15.88 g]

Configuration

Package Type Connectorized
Input Connector 1.0mm Female
Output Connector 1.0mm Female
Coupled Connectors 1.0mm Female



#### **Features:**

- Directional Coupler
- 20 GHz to 110 GHz Frequency Range
- 1.0 mm (W1) Connectorized Design
- Typical Coupling Value of 17±8 dB
- Max Power 1 Watt (CW)
- Directivity > 7 dB
- Typical VSWR of 1.4:1

## **Applications:**

- Test and Measurement
- Military Communications
- Commercial Communications
- Wireless Communications
- SATCOM

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





## **Environmental Specifications**

Temperature

Operating Range +0 to +70 deg C Storage Range -55 to +125 deg C

Humidity 95% at 40 °C, 96 hours, Test 103B, Condition B Shock 100 G peak sawtooth, method 213, Condition B

**Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

Notes:

1.0 mm Directional Coupler, 20 GHz to 110 GHz Rated to 1 Watt from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 1.0 mm Directional Coupler, 20 GHz to 110 GHz Rated to 1 Watt FMCP1162

URL: https://www.fairviewmicrowave.com/1.0mm-0-db-20-ghz-to-110-ghz-fmcp1162-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020





