

30 dB Fixed Attenuator SMA Male To SMA Female Up To 4 GHz Rated To 25 Watts With Black Aluminum Heatsink Body

Fairview Microwave carries a broad selection of fixed attenuators with a wide range of attenuation levels, frequency ranges, and power dissipation ranges. Also known as RF pads, RF microwave attenuators lower the amplitude of a signal (or attenuate) a known amount. These attenuator pads can be used in a wide variety of applications including reducing a signal level to protect measurement equipment or other circuitry, extending the range of power meters and amplifiers, and impedance matching circuits by reducing the VSWR seen by adjacent components. RF attenuators can prevent signal overload in amplifiers, receivers and detectors, adjusting the signal level to a range that is optimal.

Few RF components are as commonly used as fixed coaxial attenuators, and Fairview Microwave carries one of the largest in-stock varieties and ships them same day. The SA4S25-30 is a 30 dB Fixed Attenuator that operates from DC to 4 GHz and is rated to 25 Watts. The versatile coaxial package uses SMA male to SMA female connectors and is also REACH and RoHS compliant. The Black Anodized Aluminum Heatsink body allows for efficient heat dissipation under high power usage conditions.

Electrical Specifications

| Description | Min | Тур | Мах | Units | |
|---|--|------------|--|--------|--|
| Frequency Range | DC | | 4 | GHz | |
| Impedance | | 50 | | Ohms | |
| Nominal Attenuation | | 30 | | dB | |
| Attenuation Accuracy | | 1 | | dB | |
| VSWR | | | 1.25:1 | | |
| Input Power, CW | | | 25 | Watts | |
| rated at +25°C, derate | ed linearly to 2 | 2.5W at +1 | 25°C | | |
| Input Power, Peak | | | 5 | kWatts | |
| 5µs pulse, 0.25% duty | cycle | | | | |
| | | | | _ | |
| chanical Specificati Size Length | ons | 2 75 in | [69 85 mm] | | |
| Width/Diameter Height | 2.75 in [69.85 mm] 1.5 in [38.1 mm] 1.46 in [37.08 mm] | | | | |
| Weight Body Material and Platin | 0.316 lbs [143.34 g] ng Black Anodized Aluminum Heatsin | | | | |
| Configuration Design | | | Fixed, Bidirectional Connectorized Module | | |





Features:

- Bidirectional
- DC to 4 GHz Frequency Range
- Attenuation 30±1 dB
- Max Power 25 Watts (CW)
- VSWR < 1.25:1

Applications:

- Instrumentation
- Precision measurements
- Prototyping and characterization
- Production systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com Fairview Microwave

an INFINIT[®] brand



Connectors

| Description | Connector 1 | Connector 2 | |
|----------------------------|----------------------------|----------------------------|--|
| Туре | SMA Male | SMA Female | |
| Connector Spec. | MIL-STD-348A | MIL-STD-348A | |
| Contact Material & Plating | Beryllium Copper, Gold | Beryllium Copper, Gold | |
| Body Material & Plating | Passivated Stainless Steel | Passivated Stainless Steel | |

Environmental Specifications

Temperature Operating Range


-55 to +125 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Typical Performance Data



30 dB Fixed Attenuator SMA Male To SMA Female Up To 4 GHz Rated To 25 Watts With Black Aluminum Heatsink Body from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 30 dB Fixed Attenuator SMA Male To SMA Female Up To 4 GHz Rated To 25 Watts With Black Aluminum Heatsink Body SA4S25-30


URL: https://www.fairviewmicrowave.com/30db-fixed-attenuator-sma-male-sma-female-25-watts-sa4s25-30-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

an INFINIT® brand





301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689