

SMH1112NR-20 DATA SHEET

WR-112 Standard Gain Horn With N Female Input and 20 dB Typical Gain Operating Within 7.05 GHz to 10 GHz Frequency Range

Configuration

Design Pattern Polarization Coaxial Interface WR-112 Standard Gain Horn Directional Linear N Female

1.25:1

Electrical Specifications

| Description | Min | Тур | Мах | Units |
|------------------------------|-------|------|-----|---------|
| Frequency Range | 7.05 | | 10 | GHz |
| Impedance | | 50 | | Ohms |
| Waveguide Standard Gain Horn | | | | |
| Gain | | 20 | | dB |
| Horizontal 3dB Beam \ | Nidth | 19.3 | | Degrees |
| Vertical 3dB Beam Wic | lth | 19.3 | | Degrees |

Waveguide to Coaxial Adapter

Input VSWR

| Mechanical | Specificati | ons |
|------------|-------------|-----|
| C ' | | |

| Size | |
|----------------|--------------------|
| Length | 12.4 in 314.96 mm |
| Width/Diameter | 4.97 in 126.24 mm |
| Height | 3.64 in 92.46 mm |
| Weight | 0.895 lbs 405.97 g |
| | |

RF Connector Type

N Female

Waveguide InterfaceWaveguide SizeWR-112Body Material and PlatingAluminum

Environmental Specifications

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:



Fairview Microwave 1130 Junction Dr. #100 Allen, TX 75013 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com






WR-112 Standard Gain Horn With N Female Input and 20 dB Typical Gain Operating Within 7.05 GHz to 10 GHz Frequency Range from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: WR-112 Standard Gain Horn With N Female Input and 20 dB Typical Gain Operating Within 7.05 GHz to 10 GHz Frequency Range SMH1112NR-20


URL: https://www.fairviewmicrowave.com/wr-112-standard-gain-horn-20-db-n-smh1112nr-20-p.aspx



1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689







| FAIRVIEW MICROWAVE INC. Allen, tx 75013 www.fairviewmicrowave.com | NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm]. | | | | | |
|--|---|-------|------|-----------------|--------|------|
| WR-112 Standard Gain Horn With N Female Input and 20 dB Typical Gain Operating Within 7.05 GHz to 10 GHz Frequency Range | DWG NO SMH112NR-20 | | | CAGE CODE 3FKR5 | | |
| | CAD FILE 040416 | SHEET | SCAL | E N/A | SIZE A | 5568 |

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689